#### §76.616

program into the daily activities of existing service personnel in the discharge of their normal duties will generally cover all portions of the system and will therefore meet this requirement. Monitoring equipment and procedures utilized by a cable operator shall be adequate to detect a leakage source which produces a field strength in these bands of 20 uV/m or greater at a distance of 3 meters. During regular monitoring, any leakage source which produces a field strength of 20 uV/m or greater at a distance of 3 meters in the aeronautical radio frequency bands shall be noted and such leakage sources shall be repaired within a reasonable period of time.

NOTE 1 TO §76.614: Section 76.1706 contains signal leakage recordkeeping requirements applicable to cable operators.

[65 FR 53616, Sept. 5, 2000]

### § 76.616 Operation near certain aeronautical and marine emergency radio frequencies.

(a) The transmission of carriers or other signal components capable of delivering peak power levels equal to or greater than  $10^{-5}$  watts at any point in a cable television system is prohibited within 100 kHz of the frequency 121.5 MHz, and is prohibited within 50 kHz of the two frequencies 156.8 MHz and 243.0 MHz.

(b) At any point on a cable system from 405.925 MHz to 406.176 MHz analog transmissions are prohibited from delivering peak power levels equal to or greater than  $10^{-5}$  watts. The transmission of digital signals in this range is limited to power levels measured using a root-mean-square detector of less than  $10^{-5}$  watts in any 30 kHz bandwidth over any 2.5 millisecond interval.

[69 FR 57862, Sept. 28, 2004]

## § 76.617 Responsibility for inter-

Interference resulting from the use of cable system terminal equipment (including subscriber terminal, input selector switch and any other accessories) shall be the responsibility of the cable system terminal equipment operator in accordance with the provisions of part 15 of this chapter: provided,

however, that the operator of a cable system to which the cable system terminal equipment is connected shall be responsible for detecting and eliminating any signal leakage where that leakage would cause interference outside the subscriber's premises and/or would cause the cable system to exceed the Part 76 signal leakage requirements. In cases where excessive signal leakage occurs, the cable operator shall be required only to discontinue service to the subscriber until the problem is corrected.

[53 FR 46619, Nov. 18, 1989]

### §§ 76.618-76.620 [Reserved]

# § 76.630 Compatibility with consumer electronics equipment.

(a) Cable system operators shall not scramble or otherwise encrypt signals carried on the basic service tier. Requests for waivers of this prohibition must demonstrate either a substantial problem with theft of basic tier service or a strong need to scramble basic signals for other reasons. As part of this showing, cable operators are required to notify subscribers by mail of waiver requests. The notice to subscribers must be mailed no later than thirty calendar days from the date the request waiver was filed with the Commission, and cable operators must inform the Commission in writing, as soon as possible, of that notification date. The notification to subscribers must state:

On (date of waiver request was filed with the Commission), (cable operator's name) filed with the Federal Communications Commission a request for waiver of the rule prohibiting scrambling of channels on the basic tier of service. 47 CFR 76.630(a). The request for waiver states (a brief summary of the waiver request). A copy of the request for waiver is on file for public inspection at (the address of the cable operator's local place of business).

Individuals who wish to comment on this request for waiver should mail comments to the Federal Communications Commission by no later than 30 days from (the date the notification was mailed to subscribers). Those comments should be addressed to the: Federal Communications Commission, Media Bureau, Washington, DC 20554, and should include the name of the cable operator to